PC CADDIE cash register on iPod Touch 5G or iPhone 5

The PC CADDIE handheld POS system can now also be conveniently used on the iPod/iPhone/iPad:



This requires the iTap RDP software, which should be configured as follows:

First, the software must be downloaded and installed from the Apple Store, then the iPod's home screen can look like this, for example:



Configure iTap RDP

Firstly, a "bookmark" must be created to access the server. This is usually done via "Add manual bookmark" - the entry "Handheld 1" has already been created here. If an entry already exists, tap the arrow on the right to adjust the configuration if necessary.

iPod ♀ 13:05	(e) 100
Q Type name or address to find com	iput
Search Results	
No Search Results	
Bookmarks	
iTap mobile RDP Testser.	횐
e demo.pccaddie.com	٥
Handheld 1	۲
■: Username: GOLF\Handheld1	-
Add Manual Bookmark	>
Global Settings	
Settings	>
Extensions	>
Set Lock Code	>

The "Label" can be freely selected for the other settings - host, port and gateway (a gateway is rarely used) should be specified by the administrator of the IT environment.

Pod 🜩 13:05	@ 100	
Cancel Bookm	ark Save	
Host		
Label:	Handheld 1 >	
Host:		
Port	Default >	
Use System Proxy:	$\bigcirc \bigcirc$	
Gateway:	•••• >	
 TS Gateway server is reachable TS Gateway security Credentials 		
Credentials: GOL	.F\Handheld1 >	
Store Credentials:		
Settings		

If you scroll further down, the resolution for "Screen" is particularly important, and "Remember Zoom" should also be activated:

Pod 🗢 13:	05 🛞 📾
Cancel Book	mark Save
Use System Proxy:	: 00
Gateway:	· · · · ·
 TS Gateway server is reachable TS Gateway security Credentials 	
Credentials: G	OLF\Handheld1 >
Store Credentials:	
Settings	
Screen:	272x480x16 >
Remember Zoom:	
Advanced	>

The option to enter a customised screen resolution can be found at the bottom under "Screen":

iPod Ģ	13:05	(i) 100
Bookmark	Screen	
Normal (1	024x768)	
720p (128	0x720)	
Large (12	80x960)	
Larger (12	280x1024)	
Portrait (9	60x1440)	
Landscap	e (1440x960)	
Huge (160	0x1200)	
1080p (19	20x1080)	
Full HD (1	920x1200)	
Retina (20)48x1536)	
Custom (2	272x480)	~

Under "Advanced", no adjustments need to be made to the upper points at first...

iPod 🤤	13:06 🔘	9
Bookmark A	dvanced	
Connection		
Console:	$\bigcirc \circ \bigcirc$	
Sound:	Play on Device	>
Performance		>
Keyboard:	Automatic	>
Security Leve	I: NLA	>
Automatic Re	connect: 30 Min	>
VDI Informati	on empty	>
Remote Prog	ram:	>
User Interface	e	
Border:	Off	>

...further down, however, the "Utility Bar" setting must be set to "Initially Off" and, above all, the "Mouse Mode" must be set to "Draw Mode":

Pod 🗢 13:06	() (
Bookmark Advance	ed
VDI Information	empty 🔉
Remote Program:	>
User Interface	
Border:	Off >
Status Bar:	$\bigcirc \bigcirc$
Utility Bar:	Initially Off
Mouse Mode:	Draw Mode >
Swap Mouse Buttons:	$\bigcirc \bigcirc$
Sticky Modifiers:	$\bigcirc \bigcirc$
Reduce Lag (at cost of throu	$\bigcirc \bigcirc$
Connection Tests:	

In the further "Global Settings" (accessible from the iTap RDP main menu), the gateways are stored if required. It can be useful to define the previously defined connection as "Autostart" here - then simply less can "go wrong".



Use cash register

It is now easy to start the PC CADDIE cash register dial-in. PC CADDIE then appears with the customer list of the cash register, preceded by the password prompt if necessary. If you tap the screen briefly with three fingers at the same time, the "Utility Bar" appears at the top:

Help 🏭 🦯 🚺 💷 🔹
Tisch/Gast Buchungen Funktionen
Fiker 🗆 Bediener 🔽 Kasse 🛛 Tisch
Tisch 22 5,50 seka
Tisch/Gast (FS
QWERTZUIOPÜ8
A S D F G H J K L Ô Ä -
Y X C V B N M [] . 0 3

The first time you use it - after you have dragged the screen image to the correct size once - you should block any further resizing with the lock icon at the top.

You will also find the following symbols from left to right:

- Call up help (probably not so important for end users)
- Show keyboard (can also be done by swiping down with three fingers but our keyboard is probably better here, it actually works quite well...)
- **Draw mode** It is important that this is set. There may be two other symbols here, but they are unsuitable for handheld operation. If the operation seems to be delayed, it is often due to this.
- Lock zoom
- Option if you have several screens not important for us
- **Disconnect the connection** especially if you have activated Autostart and want to return to the configuration.

Further operation is as generally described!